

Parts List

Below is a list of all parts used in the amp, minus hookup wire and nuts and bolts. There are some suggested suppliers in the rightmost column, but of course there are always alternatives. Many people swear by certain high-quality components, but the difference that these make is up to each individual listener. For high grade audiophile-quality parts, check out Angela Instruments (angela.com), Parts Connexion (partsconnexion.com), Antique Electronic Supply (tubesandmore.com), and/or Michael Percy (percyaudio.com).

| Audio Circuit | | | |
|--|--------------------|---------------------|---|
| Part | Part No. | Quantity | Supplier(s) |
| 8 pin tube socket | P-ST8-250MB | 4 | tubesandmore.com |
| 9 pin mini tube socket | P-ST9-211 | 2 | Tubesandmore.com |
| Dual Triode | T-5965-A | 2 | tubesandmore.com |
| Power Tubes | 6V6GT | 4 (2 Matched Pairs) | Parts Connexion tubedepot.com tubesandmore.com |
| 0.47uF coupling caps (0.33uF are good too) | C-PD47-400 | 4 | tubesandmore.com |
| 100k Ω stereo pot | R-V100KD-N | 1 | Tubesandmore.com |
| Output Transformer | Hammond 125D | 2 | Parts Connexion (partsconnexion.com) |
| 120k Ω 2W resistors | Kiwame 66234 | 6 | Parts Connexion Digikey.com |
| 130k Ω 2W resistor | Kiwame 66235 | 2 | Parts Connexion Digikey.com |
| 15 Ω 2W resistor | Generic metal film | 2 | Digikey.com |
| 27k Ω 3W resistor | PPC27KW-3JCT-ND | 2 | Digikey.com |
| RCA input jacks | SC1319-ND | 1 pair | Digikey.com |
| 100 Ω 2W resistor | Generic metal film | 4 | Digikey.com |
| 100k Ω 2W resistor | Generic metal film | 4 | Digikey.com |

| Power Supply | | | |
|----------------------------------|---------------------|-----------------|--|
| Part | Part No. | Quantity | Supplier(s) |
| 0.01 uF 400V cap | C-PD01-400 | 3 | Tubesandmore.com |
| 0.1 uF 400V cap | C-PD1-400 | 1 | Tubesandmore.com |
| Positive Supply Transformer | Hammond 167G120 | 1 | Digikey.com |
| 1A Fuse | 486-1338-ND | 1 | Digikey.com |
| Fuse holder and power jack combo | Q201-ND | 1 | Digikey.com |
| Rectifier Diodes | UF1007 | 10 | Digikey.com partsconnexion.com |
| Negative Supply Transformer | TE62045-ND | 1 | Digikey.com |
| 33uF cap | P5942-ND | 3 | Digikey.com |
| 56uF cap | LGU2G560MEL Y | 1 | Digikey.com |
| 100uF cap | 493-2783-ND | 1 | Digikey.com |
| 1uF cap | 493-1226-ND | 1 | Digikey.com |
| 220uF cap | P11655-ND | 2 | Digikey.com |
| 120uF cap | | | Digikey.com |
| 1kΩ resistor | PPC1.0KW- 2CT-ND | 1 | Digikey.com |
| 4.7kΩ resistor | PPC4.7KW- 2CT-ND | 1 | Digikey.com |
| 10kΩ bias pot | Generic | 2 | Locally obtained, can be ordered at: Digikey.com Tubesandmore.com |
| 15kΩ resistor | PPC15KW-2CT- ND | 2 | Digikey.com |
| Enclosure | Hammond 1444- 30 | 1 | A1parts.ca |